

# SERVICE BULLETIN



No. : VSB2001-0034

Date : 2001-08-02

Model	Factory	Factory Model	Suffix	Model No.	Factory	Factory Model	Suffix	Model No.
	EKHQ	LN-15A10	APZMZ	ZLD15A1				
Buyer	Buyer Name	Buyer Code	Buyer Name	Buyer Code	Buyer Name	Buyer Code		
	LGEAI	US000002	ZENITH	US007515				
EFFECTIVE DATE	2001-08-01		EFFECTIVE FROM(SERIAL NO.)			Immediately		
Subject	Change in parts/numbers/specs, upgrade MICOM and change related parts							

No.	Loc No.	Before Change		After Change		Note	K-Code	Remark
		Part No	DESC./SPEC.	Part No	DESC./SPEC.			
1	IC101	OIZZVC0007E	IC,DRAWING / M37274EASP 52S DIP 52 BK US	OICTMMI004A	/	A	4	CHANGE
2	C108	OCH5080K116	Capacitor, Ceramic ,Ch / C2012C0G1H080DT 8pF	OCH5120K416	/	A	1	CHANGE
3	L101	OLA0152K119	INDUCTOR,AXIAL LEAD / 15UH 10% A 2.3 X 3.4	OLA0122K119	/	A	1	CHANGE
4	IC901	OIIT323000A	IC,ITT / VPC3230D 80P PQFP BK COMB FILTER VIDEO PROCESSOR	OIIT323000B	/	A	4	CHANGE
5	IC606	OISH092100A	IC,POWER MANAGEMENT / PQ09RF21 4P 9V S/W R	OISH092100B	/	A	4	CHANGE
6	IC607	OISH092100A	IC,POWER MANAGEMENT / PQ09RF21 4P 9V S/W R	OISH092100B	/	A	4	CHANGE

## Reason Of Change

- MICOM (IC101) CHANGE / MICOM is changed from OTP to MASK.  
C108 and L101 are changed with MICOM to adjust OSD position.  
If OSD deviation occurs after replacing MICOM, change C108 and L101.
- IC901 Change Version Upgrade. When replacing IC901 with new one, please replace the MICOM at the same time.
- IC606 and IC607 Change / Substitution

\*\* FILE THIS SERVICE BULLETIN WITH YOUR SERVICE MANUAL

NOTE(**) : INTERCHANGEABILITY CODE				KEY-WORD CODE
	Parts	Set		
A	Original	Early	Original or new parts may be used in early or late production sets. Use original parts until exhausted, then stock new parts.	1. To improve performance 2. To improve productivity
	New	Late		
B	Original	Early	Original parts may be used in early production sets only. New parts may be used in early or late production sets. Use original parts where possible, then stock new parts.	3. To improve reliability 4. Change of material or dimension
	New	Late		
C	Original	Early	New parts only may be used in early or late production sets. Stock new parts.	5. Addition 6. Deletion
	New	Late		
D	Original	Early	Original parts only may be used in early production sets. New parts may be used in late production sets only. Stock original and new parts.	7. Correction
	New	Late		

CHIEF ENGINEER , *approved*  
Factory.